

SMARTBUG

An Intelligent Monitor for the 6800

SMARTBUG - AN INTELLIGENT MONITOR FOR THE 6800

INTRODUCTION

SMARTBUG is a 1024 byte monitor program which may be used in most systems using the Motorola 6800 microprocessor. It was designed primarily to replace the MIKBUG ROM used in many systems including the Southwest Technical Products 6800 microcomputer. SMARTBUG is available from SMOKE SIGNAL BROADCASTING on a 2708 EPROM. In order to implement SMARTBUG in the SWTPC 6800 microcomputer system, SMOKE SIGNAL BROADCASTING has developed the P-38 series of EPROM boards. These boards are equipped with SMARTBUG and contain room for seven more 2708's so that the user can expand the monitor at any time.

Most of the SMARTBUG subroutines start at the same address locations as the functionally equivalent MIKBUG subroutines. Thus, most programs designed to run with MIKBUG should require little, if any, modification to run with SMARTBUG.

One major advantage of SMARTBUG is that it is available on a 2708 Eraseable-Programmable Read Only Memory Chip. This means that the user may easily change the monitor to suit his individual system requirements simply by re-programming the 2708.

WHY SMARTBUG?

SMARTBUG has several new features not found in MIKBUG which make system operation easier; however, these are not the primary reasons for SMARTBUG, but are added bonuses. MIKBUG handles serial I/O through the 6820 Parallel Interface Adapter which was designed for 8 bit parallel I/O and not serial I/O. MIKBUG requires the 6800 microprocessor to wait in timing loops while inputting or outputting data through the PIA. Thus, while the processor is writting a character, it cannot check to see if the user wishes to input a character at the same time. This limitation becomes quite noticeable to the user when trying to interrupt a program listing in BASIC (or any program that checks for user input while outputting data) by typing "CONTROL C". Many "C" keys have been worn out trying to get the program to recognize the user input. Also, while the processor is spinning its wheels in I/O timing loops, it cannot be doing any other work although this is usually unimportant except in real-time applications requiring fast servicing of interrupt requests.

SMARTBUG handles I/O through the 6850 Asynchronous Communications Interface Adapter. The 6850 was designed specifically to handle serial data. When writting data to the 6850, all

the microprocessor needs to do is check to see that the 6850 is ready to receive data and then write an 8 bit word to the 6850 in parallel form over the system data bus. This takes only a few instructions and very little time. While the 6850 is converting the parallel data received from the microprocessor to serial and sending it to the output device, it can simultaneously receive data. Thus, if you are running BASIC and type a "CONTROL C", the processor is "instantaneously" able to respond to your interrupt the first time you type "CONTROL C".

Another advantage of handling serial I/O through an ACIA is that baud rates in excess of 19,200 can be accomodated compared to a maximum baud rate of about 1200 baud that can be handled by MIKBUG.

WHY MIKBUG?

To the experienced hobbiest who has used MIKBUG, the limitations of handling serial I/O through a 6820 parallel I/O chip are intuitively obvious. If you are a newcomer, just accept it on faith that only a very strange person would use a 6820 for serial I/O instead of a 6850 in a general purpose microcomputer system. The question that is often asked is: "Why would a big company like Motorola do such a silly thing?". The answer is that in 1974 when MIKBUG was written, the 6850 was not yet in production and the 6820 was. In order to introduce the first 6800 evaluation kit, it was necessary to handle the serial I/O through a 6820 and MIKBUG was a very clever little device used to demonstrate how easy it was to use the 6800 microprocessor.

HARDWARE REQUIREMENTS

SMARTBUG "talks" through a 6850 ACIA which should be located at $8008 and $8009. It also requires RAM at $A000 through $A06B. SMARTBUG itself is located at $E000 through $E3FF. In order to have the reset and interrupt vectors operate without external ROM, it is necessary to have SMARTBUG located at $FC00 through $FFFF in addition to $E000 through $E3FF. The SMOKE SIGNAL BROADCASTING P-38 series of EPROM boards has a switch to allow SMARTBUG to occupy both of these areas or only the $E000 through $E3FF area when using another 2708 in the $FC00 through $FFFF area. To locate a 6850 ACIA at $8008 and $8009, owners of the SWTPC 6800 should purchase a MP-S board and place it in I/O slot number 2. The MP-C control board in slot number 1 is no longer used and should be removed from the machine.

USE OF HIGH BAUD RATES

The maximum baud rate useable with MIKBUG is about 1200 baud. With SMARTBUG, it is possible to use baud rates of at least

19,200; however, for baud rates in excess of about 1200 baud, it may be necessary to change the crystal in the SWTPC 6800. The MC14411P baud rate generator chip used in the SWTPC 6800 is designed to use a crystal frequency of 1.8432 MHz. The crystal supplied with the SWTPC 6800 is a few percent lower in frequency due to an anomoly of MIKBUG. If you wish to take full advantage of SMARTBUG and use it's high baud rate capability, you may need a crystal of the correct frequency. Also, it will be necessary to bring the desired baud rate line out from the baud rate generator chip on the CPU board in place of one of the lower baud rates that you are not using. This requires a foil cut and jumper on the CPU card. Consult the CPU card instruction manual and the MC14411P data sheet to determine the correct locations for your particular application.

SOFTWARE OPERATION

RESET

Pressing the reset button on the SWTPC 6800 will cause SMARTBUG to output a carriage return, line feed and an asterisk (*) to the system terminal. As in MIKBUG, the asterisk is the prompt character; and, when it appears, SMARTBUG is waiting for the user to enter a command. One of the advantages of having your monitor in EPROM is that you are able to customize the monitor to your system. When SMARTBUG prompts with an asterisk, it is actually outputting the character string located at $E3F0 through $E3F6. If you are using a non-scrolling terminal such as the CT-1024, you may wish to change one of the null (00) characters in this string to an "Erase to End of Line" character ($15 in the case of the CT-1024).

COMMANDS

After being prompted with an asterisk, the user may enter any valid SMARTBUG command. All SMARTBUG commands are single-letter commands followed, in some cases, by address information. The valid command letters are A, B,C,D,E,G, H,I,J,K,L,M,N,P,Q,R,T,X,4. Entering any other character will cause SMARTBUG to prompt again with an asterisk.

"R" REGISTERS

Typing "R" will cause SMARTBUG to display the various registers in the 6800 in the following format.

```
*R CC BB AA XXXX PCPC SPSP
```

Throughout this manual, user input is indicated by underlined characters. Output from SMARTBUG is not underlined.

CC is the two hex digits representing the contents of the Condition Code Register
BB is the contents of the B Accumulator
AA is the contents of the A Accumulator
XXXX is the contents of the Index Register (4 hex digits)
PCPC is the contents of the Program Counter
SPSP is the contents of the Stack Pointer

"A" EXAMINE AND CHANGE THE A ACCUMULATOR

Entering an "A" after the * prompt character will cause the contents of the A Accumulator to be displayed. To change the contents of the A Accumulator, simply type two hex characters. Type a carriage return to return to SMARTBUG without altering the contents of the A Accumulator. A sample format is shown below.

*A XX YY

where XX is the old contents of the A Accumulator and YY is the new contents entered by the user.

"B" EXAMINE AND CHANGE THE B ACCUMULATOR

"B" allows the user to examine and change the contents of the B Accumulator and operates in the same manner as the "A" command.

"C" EXAMINE AND CHANGE THE CONDITION CODE REGISTER

"C" allows the user to examine and change the Condition Code Register and operates in the same manner as the "A" command.

"X" EXAMINE AND CHANGE THE INDEX REGISTER

"X" allows the user to examine and change the contents of the Index Register. This command operates in the same manner as the "A" command except that four hex characters are required for the "X" command instead of two.

"M" MEMORY EXAMINE AND CHANGE

The "M" command allows the user to examine any memory location and to change any memory location occupied by RAM memory. To examine a memory location, type "M" followed by the four hex digits of the memory location you wish to examine.

EXAMPLE: *M 0100
*0100 7E BD
*0101 E1

In the above example, the user typed "M" followed by "0100". SMARTBUG then typed *0100 7E. 7E was the old contents of 0100. The user then typed "BD", thus changing the contents of 0100 to BD. SMARTBUG then proceeded to show the user the contents of 0101.

To change a memory location, it is only necessary to type the two hex digits representing the new data. To return to SMARTBUG without changing the data, type a carriage return. To examine the following location without changing the present location, hit the SPACE BAR. To examine the previous memory location, type "U" for up.

GO TO USER'S PROGRAM

Two commands are provided to transfer control from SMARTBUG to a user's program. The "G" command which operates in the same manner as the "G" command in MIKBUG and a new "J" command.

"G" GO TO LOCATION CONTAINED IN $A048 and $A049

To use the "G" command, first use the "M" command to put the starting address of the program into memory locations $A048 and $A049. Then type "G". SMARTBUG will then jump to the location contained in $A048 and $A049. This command is useful when you will enter the program several times from SMARTBUG. When you only intend to enter the program from SMARTBUG once, the "J" command is more convenient.

"J" JUMP TO LOCATION XXXX

Typing "J" "XXXX" where XXXX are four hex digits will cause SMARTBUG to transfer program control to that location. EXAMPLE: *J 01A0 will cause SMARTBUG to jump to $01A0 and begin executing whatever program was previously stored beginning at that location.

"I" INSERT

FORMAT: I XXXX YYYY ZZ EXAMPLE: *I 0000 3FFF 3F
This command will insert the two hex digits "ZZ" into memory locations "XXXX" through "YYYY". In the example, memory locations $0000 through $3FFF will now contain $3F. In debugging a new program, it is often desireable to store $3F (software interrupt) in all your memory prior to loading and executing the program. If the program inadvertantly

transfers outside the program area, it will encounter a software interrupt, display the CPU registers and return to SMARTBUG. This command can also be used to clear blocks of memory by storing "00" into specified areas of memory.

"Q" QUICKSTART

This command is for the convenience of those people using the SMOKE SIGNAL BROADCASTING BFD-68 Disc System. Typing "Q" does the same thing as typing "J 8020". SMARTBUG transfers control to $8020 which is the beginning address of the routine that boots in the disc operating system from a cold start.

"D" DISC

Typing "D" transfers control from SMARTBUG to $7283 which is the warmstart address of DOS68, the disc operating system used with the BFD-68 disc system. This provides a convenient means of re-entering the DOS68 monitor from SMARTBUG when DOS68 has previously been booted in from disc and is resident in memory. Those people using the optional version of DOS68 located between D000 and DFFF will want to re-program the 2708 and change location $E3DF from $72 to $D2. Typing "D" will then trasfer program control to $D283 which is the warmstart address of the optional version of DOS68.

"E" ECHO, "N" NO-ECHO, "H" HARDCOPY

RAM location $A00B is a "flag" location that determines whether INEEE will echo back characters typed on the terminal and whether OUTEEE will output to the system terminal connected to I/O port number 2 (ACIA at $8008 and $8009) or jump to an external output routine. The external output routine would normally be a routine to drive a hardcopy printer. INEEE is a subroutine located at $E1AC that waits for a character input from the system console and returns that character input in the A accumulator. OUTEEE is located at $E1D1 and causes a character in the A accumulator to be transmitted to the system console (or to the external print routine).

When hitting "RESET" or otherwise entering SMARTBUG at $E0D0, location $A00B is cleared. Typing an "E" will also clear this location. When location $A00B contains a "00", all input through INEEE will be echoed through the system console and calls to OUTEEE will result in output to the system console and not a jump to an external printer output routine.

NOTE: Many programs have been written that re-enter MIKBUG upon completion of the program at "START" location $E0D0.

Normally, it is better to re-enter MIKBUG or SMARTBUG at "CONTRL" location $E0E3. Entering at "CONTRL" will not re-initialize $A00B to the ECHO mode, but will leave it in the mode last selected by the user or the user's program. This is usually more desireable. While MIKBUG does not have an echo control feature, there are some other reasons why it is usually better to re-enter MIKBUG or SMARTBUG at $E0E3 rather than $E0D0. Also, remember that hitting "RESET" restores the echo. Unless this is your desired mode of operation, you will have to type "N" or "H" after pressing "RESET".

Any positive number ($01 through $7F) stored in $A00B will cause INEEE not to echo the character inputted through INEEE and OUTEEE will not jump to an external print routine. Typing "N" stores a $4E in location $A00B and, thus, suppresses the echo.

Any negative number ($80 through $FF) stored in $A00B will cause OUTEEE to jump to $A04A before anything is transmitted to the terminal device. Typing "H" stores a $B8 in location $A00B and, therefore, will cause OUTEEE to jump to $A04A. Any user wishing to use the "H" command will have to put a jump to his printer routine location in location $A04A, $A04B and $A04C prior to using this feature. Those SMARTBUG users having a SMOKE SIGNAL BROADCASTING P-38 series EPROM board will probably want to put their printer routine in EPROM. Then the printer routine will always be available without having to load it into RAM each time the system is powered up. The next EPROM location available on the P-38 board is $E400 through $E7FF. We suggest standardizing on $E600 as the beginning location of the print routine. This leaves $E400 through $E5FF available for extended monitor routines. If you do put your printer routine at $E600, you will probably want to change SMARTBUG location $E1D7 from $A0 to $E6 and location $E1D8 from $4A to $00. This will cause OUTEEE to jump directly to your routine at $E600 instead of to $A04A. This again points out the advantage of having the system monitor in EPROM rather than ROM. With EPROM, it is easy to customize the system monitor to your unique system requirements.

If you want OUTEEE to output both to the system console as well as to your separate hardcopy device when in the "H" mode, your print routine should end with a jump to $E1D9. Otherwise, it should end with a "RTS" ($39).

CONTROL OF THE ECHO FUNCTION FROM THE USER'S PROGRAM

Several programs such as BASIC and DOS68 turn the MIKBUG echo off prior to jumping to INEEE and restore the echo upon return. This allows the program to echo control characters and other normally non-printable characters. This is also probably the only major area where SMARTBUG and MIKBUG are not compatible. In MIKBUG, the echo is suppressed by storing a $3C in location $8007 and is restored by storing

$34 in location $8007. Running a program that suppresses the MIKBUG echo in SMARTBUG without first modifying the echo handling routine will result in the input being double echoed unless you type a "N" prior to entering these programs. For frequently used programs, it will probably be more convenient to modify them than to remember to type "N".

To modify an existing program, we suggest that you change the instructions storing a $3C in $8007 to an "INC $A00B" (7C A0 0B) and that the instruction storing a $34 in $8007 be changed to a "DEC $A00B" (7A A0 0B). NOP's ($01) should be used to fill in the extra area used by the previous instructions.

In DOS68, the echo control is found in the ZLINEI routine. The jump to ZLINEI is found in the jump table at $72B5 (or $D2B5). Echo is turned off by the instruction sequence 86 3C B7 80 07 and turned back on by the sequence 86 34 B7 80 07. These sequences should be changed to 7C A0 0B 01 01 and 7A A0 0B 01 01 respectively. The exact location of the ZLINEI routine may vary with different versions of DOS68, but the jump table location will remain the same. This is why we ask you to go to the jump table to find ZLINEI and search through ZLINEI for this instruction sequence rather than specify the locations to be changed.

By using an increment-decrement scheme to control the echo, the user now has control of the echo even if he has selected the "H" HARDCOPY function prior to entering his program. The first part of the printer routine should test to see if $A00B contains a $B8. If it does, the routine should output data given it. If it contains a $B9, the routine should do a "RTS" without outputting the data.

"P" PUNCH FORMATTED TAPE

EXAMPLE: *P 0100 0150

The above example will cause SMARTBUG to punch a formatted tape containing the data in memory locations $0100 through $0150. The tape format is the same as the MIKBUG format and S9 is not punched at the end. This way, several areas of memory may be punched on one tape and loaded with one "L" command. At the end of the last area of memory to be punched to the tape, the user should manually type a S9 to the tape so that the "L" command will function automatically.

"L" LOAD FORMATTED TAPE

Typing "L" will turn on the system tape reader and read formatted tape produced by the "P" command. If the tape does not contain a S9 as an end of file indicator, it will be necessary for the user to manually type a S9 on the system console after the tape has been read in order to return to

SMARTBUG. The S9 causes SMARTBUG to be entered at "CONTRL". This is to be preferred over hitting "RESET" which causes entry at "START".

Unlike MIKBUG, SMARTBUG normally echoes the tape input. If the user wishes to suppress the echo when loading tape, he should type "N" prior to typing "L".

"4" JUMP TO $E400

Typing a "4" will cause SMARTBUG to jump to $E400. This command allows users of the SMOKE SIGNAL BROADCASTING P-38 series boards to expand their SMARTBUG monitor to include additional commands by installing another 2708 EPROM in the $E400 through $E7FF socket on the board. The user can accomodate additional commands by having a routine starting at $E400 that asks for an additional character input and then executes whatever command is specified by that second character. Using this approach, all regular SMARTBUG commands would continue to be one character commands and all extended commands would be two character commands with the number "4" being the first character.

We would very much appreciate a copy of any extended commands you may develop. Naturally, we would prefer a fully-commented source listing; however, don't be embarrassed to send just the object code along with a brief functional description. After all, it seems most of us write programs first and document them later (and then, only if absolutely necessary).

"K" BREAKPOINT

The "K" command is a tool to allow the programmer to step through his program a few steps at a time in order to inspect his program at these intermediate steps to see if the program is, indeed, operating as it was so carefully designed to do. To use the "K" command, first load the starting address of the program into memory locations $A048 and $A049 using the "M" command. Next decide where you want the first breakpoint. Then type "K" followed by the four hex digits representing the address at which the breakpoint is to be inserted. After entering the fourth digit, SMARTBUG will jump to the location previously stored in $A048 and $A049 and execute the program until it encounters the breakpoint (if it ever does). When the breakpoint is encountered, SMARTBUG will display the contents of the registers in the same format as the "R" command. To continue the program at the point it was interrupted, simply type "G". To pick up at this point and continue to a second breakpoint, type "K" followed by a new breakpoint address.

SMARTBUG uses the "SWI" ($3F) instruction to set a breakpoint; thus, a breakpoint may not be set in an area of Read-Only-Memory. SMARTBUG remembers the instruction stored in the breakpoint location and automatically restores that instruction

after encountering the breakpoint. If the program "gets lost" and the breakpoint is not encountered, the instruction will not be restored and will have to be manually restored by the user.

"T" TRACE MODE

Typing a "T" followed by a four digit hexadecimal address puts SMARTBUG in the single-step trace mode. This allows the user to step through a program in RAM one step at a time and to examine and change the registers after each step. Stepping to a ROM location will cause SMARTBUG to return to the regular command mode and prompt with an asterisk. After typing "T" followed by four hex digits, SMARTBUG will type the current contents of the registers followed by the specified address and the command to be executed at that address. No asterisk prompt character is issued which indicates that SMARTBUG is in the TRACE mode. Prior to executing the next instruction, the user may change the A, B, C or X registers with the A, B, C or X commands. When ready to execute the next instruction, hit the SPACE BAR. To return to the regular SMARTBUG mode, hit the carriage return. Following is the trace output from a very short program.

```
MEMORY CONTENTS:  0100 86
                  0101 43
                  0102 BD
                  0103 01
                  0104 D1
                  0105 86
                  0106 55
                  0107 3F
                  01D1 39

*T 0100
F0 33 00 E26E 0100 A049
0100 86 43
SPACEBAR
F0 33 43 E26E 0102 A049
0102 BD 01D1
SPACEBAR
F0 33 43 E26E 01D1 A047
01D1 39
B 33 48
SPACEBAR
F0 48 43 E26E 0105 A049
0105 86 55
SPACEBAR
F0 48 55 E26E 0107 A049
0107 3F
SPACEBAR
*
```

The format for the listing of the register contents is the same as in the "R" command.

IRQ AND NMI

If the system encounters an IRQ interrupt request, it will jump to the location contained in memory locations $A000 and $A001. An NMI interrupt will cause SMARTBUG to jump to the location contained in memory locations $A006 and $A007. If the user anticipates these types of interrupts, he should initialize these locations early in his program. Alternately, he can re-program the vector locations in SMARTBUG to go to permanent interrupt handling routines in his system.

COMPATIBILITY WITH MIKBUG

Every reasonable effort was made to keep the subroutines in SMARTBUG at the same beginning address locations as the functionally equivalent subroutines in MIKBUG so that programs written for MIKBUG would run in SMARTBUG without modification. As shown in the list below, all the locations of the most frequently used routines are maintained.

THE FOLLOWING LABELS IN SMARTBUG ARE FUNCTIONALLY EQUIVALENT TO THOSE IN MIKBUG AND ARE LOCATED AT THE SAME ADDRESS LOCATIONS.

IO	POWDWN	LOAD	LOAD3	LOAD11	LOAD15
LOAD19	LOAD21	C1	BADDR	BYTE	OUTHL
OUTHR	OUTCH	INCH	PDATA2	PDATA1	CHANGE
CHA51	INHEX	IN1HG	OUT 2H	OUT2HA	OUT4HS
OUT2HS	OUTS	START	CONTRL	SFE	INEEE
OUTEEE	IOV	BEGA	ENDA	NIO	SP
XHI	XLOW	TEMP	TW	XTEMP	STACK

THE FOLLOWING LOCATIONS IN MIKBUG ARE NOT FOUND AT THE SAME LOCATIONS IN SMARTBUG AND THERE MAY BE NO FUNCTIONALLY EQUIVALENT LABEL IN SMARTBUG.

PRINT	C2	MTAPE1	PUNCH	PUN11	PUN22
PUN23	PUN32	PUNT2	MCLOFF	MCL	SAV
IN1	IN3	IOUT	OUT1	IOUT2	IOS
DEL	DE	CKSM	BYTECT	MCONT	

LIMITED WARRANTEE

Any purchaser of SMARTBUG who is not satisfied with its performance may return his copy within 10 days from date of purchase for a full refund. This warrantee is in lieu of all other warrantees express or implied. SMOKE SIGNAL BROADCASTING does not warrant the suitability of SMARTBUG for any particular user application and will not be responsible for damages incidental to its use in a user system.

LICENSE CONDITIONS

Purchase of a P-38 series board which includes SMARTBUG or purchase of a SMARTBUG listing conveys to the purchaser a license to copy SMARTBUG for his own use, and not for sale or free distribution to others. No other license, express or implied, is conveyed.

LIMERICK

Mary had a little plane.
She flew it high and brisk.
Wasn't she a silly girl,
her little *

USER CONTRIBUTIONS

Any user wishing to contribute program or limerick improvements should send them to:

SMOKE SIGNAL BROADCASTING
P.O. BOX 2017
HOLLYWOOD, CA 90028

We are particularly interested in extended monitor commands for possible inclusion in a future 2K or 4K monitor program. Worthwhile contributions will also be published in future newletters with credit to the author.

E000 } SMARTBUG ROM
E3F1 }
E3F8 } INTERRUPT VECTORS
E3FF }

E400 } EXTENDED ROM
E5FF }
2600 } PRINTER ROUTINE

```
00100                          NAM    SMARTBUG

00120                  *       "SMARTBUG" - AN INTELLIGENT MONITOR
00130                  * COPYRIGHT 1977  SMOKE SIGNAL BROADCASTING

00150                          OPT    O,S
00160       8008       ACIAS   EQU    $8008
00170       8009       ACIAD   EQU    $8009
00180 E000                     ORG    $E000

00200                  * I/O INTERRUPT SEQUENCE
00210 E000 FE A000 IO          LDX    IOV
00220 E003 6E 00               JMP    X

00240                  *  NMI SEQUENCE
00250 E005 FE A006 POWDWN      LDX    NIO      GET NMI VECTOR
00260 E008 6E 00               JMP    X        GO TO NMI LOCATION

00280                  * LOAD ASCII FORMATTED TAPE
00290       E00A       LOAD    EQU    *
00300 E00A 86 55               LDA A  #$55     READER RELAY ON, ONE STOP BIT
00310 E00C B7 8008             STA A  ACIAS
00320 E00F 86 11               LDA A  #$11
00330 E011 8D 62               BSR    OUTCH    AC-30 READ CTRL
00340 E013 8D 63       LOAD3   BSR    INCH     GET CHARACTER
00350 E015 81 53               CMP A  #'S      IS IT AN "S"
00360 E017 26 FA               BNE    LOAD3    NO-LOOP TILL "S" FOUND
00370 E019 8D 5D               BSR    INCH     YES - GET NEXT CHARACTER
00380 E01B 81 39               CMP A  #'9      IS IT A "9"
00390 E01D 27 25               BEQ    LOAD21   YES - JUMP TO CONTROL
00400 E01F 81 31               CMP A  #'1      IS IT A "1"
00410 E021 26 F0               BNE    LOAD3    NO - TRY AGAIN
00420 E023 7F A06A             CLR    CKSM     YES - ZERO CHECKSUM
00430 E026 8D 2D               BSR    BYTE     GET A BYTE
00440 E028 80 02               SUB A  #2
00450 E02A B7 A06B             STA A  BYTECT   READ THIS MANY BYTES
00460                  * BUILD ADDRESS
00470 E02D 8D 18               BSR    BADDR
00480                  * STORE DATA
00490 E02F 8D 24       LOAD11  BSR    BYTE     READ NEXT BYTE
00500 E031 7A A06B             DEC    BYTECT   DECREMENT BYTE COUNTER
00510 E034 27 05               BEQ    LOAD15   IF 0, GET NEXT LINE
00520 E036 A7 00               STA A  X        ELSE, STORE DATA
00530 E038 08                  INX
00540 E039 20 F4               BRA    LOAD11
00550 E03B 7C A06A LOAD15      INC    CKSM     FORM 2'S COMPLEMENT
00560 E03E 27 D3               BEQ    LOAD3    IT SHOULD BE ZERO
00570 E040 86 3F       LOAD19  LDA A  #'?      READ ERROR - PRINT
00580 E042 8D 31               BSR    OUTCH    QUESTION MARK
00590       E044       LOAD21  EQU    *
00600 E044 7E E0E3 C1          JMP    CONTRL

00620                  * BUILD ADDRESS
00630 E047 8D 0C       BADDR   BSR    BYTE     READ 2 BYTES
```

```
00640 E049 B7 A00C        STA A  XHI      AND RETURN FROM THIS
00650 E04C 8D 07          BSR    BYTE     SUBROUTINE WITH BOTH
00660 E04E B7 A00D        STA A  XLOW     BYTES IN THE INDEX
00670 E051 FE A00C        LDX    XHI      REGISTER.
00680 E054 39             RTS

00700                * INPUT BYTE (2 HEX CHARACTERS)
00710 E055 8D 53   BYTE   BSR    INHEX    GET 1ST HEX CHAR
00720 E057 48             ASL A
00730 E058 48             ASL A
00740 E059 48             ASL A
00750 E05A 48             ASL A
00760 E05B 16             TAB
00770 E05C 8D 4C          BSR    INHEX    GET 2ND HEX CHAR
00780 E05E 1B             ABA
00790 E05F 16             TAB
00800 E060 FB A06A        ADD B  CKSM     UPDATE CHECKSUM AND
00810 E063 F7 A06A        STA B  CKSM     RETURN WITH BYTE IN
00820 E066 39             RTS             A ACCUMULATOR

00840 E067 44      OUTHL  LSR A           OUT HEX LEFT BCD DIGIT
00850 E068 44             LSR A
00860 E069 44             LSR A
00870 E06A 44             LSR A

00890 E06B 84 0F   OUTHR  AND A  #$F      OUT HEX RIGHT BCD DIGIT
00900 E06D 8B 30          ADD A  #$30
00910 E06F 81 39          CMP A  #$39
00920 E071 23 02          BLS    OUTCH
00930 E073 8B 07          ADD A  #7
00940 E075 7E E1D1 OUTCH  JMP    OUTEEE   OUTPUT A CHARACTER
00950 E078 7E E1AC INCH   JMP    INEEE    INPUT A CHARACTER

00970                * PRINT DATA POINTED TO BY INDEX REGISTER
00980 E07B 8D F8   PDATA2 BSR    OUTCH
00990 E07D 08             INX
01000 E07E A6 00   PDATA1 LDA A  X
01010 E080 81 04          CMP A  #4        END OF STRING CHARACTER
01020 E082 26 F7          BNE    PDATA2
01030 E084 39             RTS

01050                * CHANGE MEMORY
01060 E085 8D C0   CHANGE BSR    BADDR    GET MEMORY ADDRESS
01070 E087 CE E3F1 CHA51  LDX    #MCL
01080 E08A 8D F2          BSR    PDATA1   PRINT C/R L/F
01090 E08C CE A00C        LDX    #XHI
01100 E08F 8D 37          BSR    OUT4HS   PRINT ADDRESS
01110 E091 FE A00C        LDX    XHI
01120 E094 8D 34          BSR    OUT2HS   PRINT OLD DATA
01130 E096 FF A00C        STX    XHI
01140 E099 8D DD          BSR    INCH     INPUT A CHARACTER
01150 E09B 81 20          CMP A  #$20     IF IT'S A SPACE
01160 E09D 27 E8          BEQ    CHA51    GET NEXT ADDRESS
01170 E09F 7E E3AD        JMP    TDEX     ELSE - GO TO TDEX
```

```
01190 E0A2 A7 00   CHA61  STA A  X        STORE NEW DATA
01200 E0A4 A1 00          CMP A  X        DID IT STORE CORRECTLY?
01210 E0A6 27 DF          BEQ    CHA51    YES - GET NEXT ADDRESS
01220 E0A8 20 96          BRA    LOAD19   NO - JUMP CONTROL

01240                   * INPUT HEX CHARACTER
01250 E0AA 8D CC   INHEX  BSR    INCH
01260 E0AC 80 30          SUB A  #$30
01270 E0AE 2B 94          BMI    C1       NOT HEX, JUMP CONTROL
01280 E0B0 81 09          CMP A  #9
01290 E0B2 2F 0A          BLE    IN1HG
01300 E0B4 81 11          CMP A  #$11
01310 E0B6 2B 8C          BMI    C1       NOT HEX
01320 E0B8 81 16          CMP A  #$16
01330 E0BA 2E 88          BGT    C1       NOT HEX
01340 E0BC 80 07          SUB A  #7
01350 E0BE 39      IN1HG  RTS

01370 E0BF A6 00   OUT2H  LDA A  X        OUTPUT 2 HEX CHAR
01380 E0C1 8D A4   OUT2HA BSR    OUTHL    OUT LEFT HEX CHAR
01390 E0C3 A6 00          LDA A  X
01400 E0C5 08             INX
01410 E0C6 20 A3          BRA    OUTHR    OUTPUT RIGHT HEX CHAR

01430 E0C8 8D F5   OUT4HS BSR    OUT2H    OUTPUT 4 HEX CHAR AND SPACE
01440 E0CA 8D F3   OUT2HS BSR    OUT2H    OUTPUT 2 HEX CHAR AND SPACE
01450 E0CC 86 20   OUTS   LDA A  #$20     OUTPUT SPACE
01460 E0CE 20 A5          BRA    OUTCH

01480                   * POWER ON SEQUENCE
01490      E0D0   START  EQU    *
01500 E0D0 8E A042        LDS    #STACK
01510 E0D3 BF A008        STS    SP
01520 E0D6 7F A00B        CLR    ECHO     ECHO ALL INPUT CHARACTERS
01530 E0D9 86 03          LDA A  #3       MASTER RESET OF ACIA
01540 E0DB B7 8008        STA A  ACIAS
01550 E0DE 86 15   INZ    LDA A  #$15     SET UP FOR 1 STOP BIT
01560 E0E0 B7 A00A INZ1   STA A  ACIAT
01570 E0E3 B6 A00A CONTRL LDA A  ACIAT    ALLOW FOR SOFTWARE CONTROL
01580 E0E6 B7 8008        STA A  ACIAS    OF ACIA CONTROL REGISTER
01590 E0E9 8E A042        LDS    #STACK
01600 E0EC 7F A011        CLR    TFLAG    TURN OFF TRACE MODE
01610 E0EF CE E3F0        LDX    #MCLOFF
01620 E0F2 8D 8A          BSR    PDATA1

01640 E0F4 8D 82          BSR    INCH     INPUT COMMAND CHARACTER
01650 E0F6 7F A014        CLR    BKFLG    CLEAR BREAKPOINT INDICATOR
01660 E0F9 16             TAB
01670 E0FA 8D D0          BSR    OUTS
01680 E0FC CE E3C3        LDX    #FUTABL  DO TABLE LOOKUP
01690 E0FF E1 00   NXTCHR CMP B  0,X      FOR COMMAND FUNCTIONS
01700 E101 27 0B          BEQ    GOODCH   MATCH FOUND
01710 E103 08             INX             NO MATCH-INC TO NEXT COMMAND
01720 E104 08             INX
```

ISR PIVIT

```
01730 E105 08                INX
01740 E106 8C E3F0           CPX   #TBLEND  END OF COMMAND TABLE?
01750 E109 26 F4             BNE   NXTCHR   NO - GET NEXT CHARACTER
01760 E10B 7E E2D9           JMP   CKCBA    YES - CHECK FOR A,B,C,X CMNDS
01770 E10E EE 01   GOODCH LDX   1,X       GET COMMAND LOCATION
01780 E110 6E 00             JMP   0,X      AND JUMP THERE
01790 E112 01                NOP            KEEP SFE AT $E113

01810              * ENTER FROM SOFTWARE INTERRUPT
01820 E113 BF A008 SFE   STS   SP         SAVE PROGRAM'S STACK POINTER
01830              * DECREMENT PROGRAM COUNTER
01840 E116 30                TSX
01850 E117 6D 06             TST   6,X
01860 E119 26 02             BNE   *+4
01870 E11B 6A 05             DEC   5,X
01880 E11D 6A 06             DEC   6,X
01890 E11F 7D A011           TST   TFLAG
01900 E122 27 63             BEQ   PRNT     IF TRACE IS OFF
01910 E124 7E E38C           JMP   SWTURN   IF TRACE IS ON

01930              * PUNCH - OUTPUT HEX FORMATTED TAPE

01950 E127 8D 74   PUNCH  BSR   LIMITS   GET LIMITS
01960 E129 86 12          LDA A #$12     AC-30 CONTRL
01970 E12B BD E075        JSR   OUTCH
01980 E12E FE A002        LDX   BEGA     THE "P" COMMAND JUMPS TO
01990 E131 FF A00F        STX   TW       PUNCH AFTER USING THE LIMITS
02000 E134 B6 A005 PUN11  LDA A ENDA+1   SUBROUTINE TO ENTER THE
02010 E137 B0 A010        SUB A TW+1     START AND STOP ADDRESSES
02020 E13A F6 A004        LDA B ENDA
02030 E13D F2 A00F        SBC B TW
02040 E140 26 04          BNE   PUN22
02050 E142 81 10          CMP A #16
02060 E144 25 02          BCS   PUN23
02070 E146 86 0F   PUN22  LDA A #15
02080 E148 8B 04   PUN23  ADD A #4
02090 E14A B7 A064        STA A MCONT    FRAME COUNT THIS RECORD
02100 E14D 80 03          SUB A #3
02110 E14F B7 A00E        STA A TEMP     BYTE COUNT THIS RECORD
02120              * PUNCH C/R,L/F,NULL,S,1
02130 E152 8D 77          BSR   CRLF
02140 E154 08             INX
02150 E155 8D 77          BSR   PDAT1
02160 E157 5F             CLR B          ZERO CHECKSM
02170              *  PUNCH FRAME COUNT
02180 E158 CE A064        LDX   #MCONT
02190 E15B 8D 25          BSR   PUNT2    PUNCH 2 HEX CHAR
02200              * PUNCH ADDRESS
02210 E15D CE A00F        LDX   #TW
02220 E160 8D 20          BSR   PUNT2
02230 E162 8D 1E          BSR   PUNT2
02240              * PUNCH DATA
02250 E164 FE A00F        LDX   TW
02260 E167 8D 19   PUN32  BSR   PUNT2    PUNCH ONE BYTE
```

```
02270 E169 7A A00E          DEC    TEMP     DECREMENT ONE BYTE
02280 E16C 26 F9            BNE    PUN32
02290 E16E FF A00F          STX    TW
02300 E171 53               COM B
02310 E172 37               PSH B
02320 E173 30               TSX
02330 E174 8D 0C            BSR    PUNT2    PUNCH CHECKSUM
02340 E176 33               PUL B           RESTORE STACK
02350 E177 FE A00F          LDX    TW
02360 E17A 09               DEX
02370 E17B BC A004          CPX    ENDA
02380 E17E 26 B4            BNE    PUN11
02390 E180 20 47            BRA    C3       GO TO CONTROL
02400 E182 EB 00   PUNT2    ADD B  X
02410 E184 7E E0BF          JMP    OUT2H
02420 E187 20 61   PRNT     BRA    PRINT

02440 E189 8D 36   BKPNT    BSR    BAD2     GET BREAKPOINT ADDRESS
02450 E18B FF A068          STX    PB2
02460 E18E A6 00            LDA A  X        SAVE INSTRUCTION AND
02470 E190 B7 A014          STA A  BKFLG    SET BREAKPOINT FLAG
02480 E193 86 3F            LDA A  #$3F
02490 E195 A7 00            STA A  X        SET BREAKPOINT
02500 E197 8D 32            BSR    CRLF
02510 E199 BE A008 CONTG    LDS    SP       RESTORE PGM'S STACK POINTER
02520 E19C 3B               RTI             GO TO USER'S PROGRAM

02540 E19D 8D 22   LIMITS   BSR    BAD2     GET FIRST ADDRESS
02550 E19F FF A002          STX    BEGA
02560 E1A2 8D 05            BSR    OUS      OUTPUT A SPACE
02570 E1A4 8D 1B            BSR    BAD2     GET SECOND ADDRESS
02580 E1A6 FF A004          STX    ENDA
02590 E1A9 7E E0CC OUS      JMP    OUTS     OUTPUT A SPACE & RETURN

02610                * INPUT ONE CHARACTER INTO A ACCUMULATOR
02620 E1AC B6 8008 INEEE    LDA A  ACIAS    TEST RECEIVE DATA REG FULL
02630 E1AF 47               ASR A           FLAG AND LOOP TILL IT IS SET
02640 E1B0 24 FA            BCC    INEEE
02650 E1B2 B6 8009          LDA A  ACIAD    GET DATA
02660 E1B5 84 7F            AND A  #$7F     ELIMINATE PARITY BIT
02670 E1B7 81 7F            CMP A  #$7F
02680 E1B9 27 F1            BEQ    INEEE    IGNORE RUBOUTS
02690 E1BB 7D A00B          TST    ECHO
02700 E1BE 2F 11            BLE    OUTEEE
02710 E1C0 39               RTS

02730 E1C1 7E E047 BAD2     JMP    BADDR    GET ADDRESS

02750 E1C4 5F      ECHON    CLR B           ECHO ALL INPUT CHARACTERS
02760 E1C5 50      PRNTON   NEG B           TURN PRINTER ON
02770 E1C6 F7 A00B ECHOFF   STA B  ECHO     DO NOT ECHO
02780 E1C9 20 41   C3       BRA    C2       GO TO CONTROL

02800 E1CB CE E3A4 CRLF     LDX    #CRLFAS  C/R L/F WITHOUT * PROMPT
```

```
02810 E1CE 7E E07E PDAT1  JMP    PDATA1   SIGNIFIES TRACE MODE

02830              * OUTPUT ONE CHARACTER FROM A-REG
02840 E1D1 7D A00B OUTEEE TST    ECHO     IF ECHO IS NEGATIVE,
02850 E1D4 2C 03          BGE    OUTCH2   GO TO PRINTER ROUTINE.
02860 E1D6 7E A04A        JMP    PRINTR
02870 E1D9 37      OUTCH2 PSH B
02880 E1DA F6 8008 OUTCH1 LDA B  ACIAS    TEST TRANSMIT DATA
02890 E1DD 57             ASR B           REGISTER EMPTY FLAG
02900 E1DE 57             ASR B           AND LOOP TILL SET
02910 E1DF 24 F9          BCC    OUTCH1
02920 E1E1 B7 8009        STA A  ACIAD    OUTPUT DATA TO ACIA
02930 E1E4 33             PUL B           RESTORE B-REG
02940 E1E5 39             RTS

02960 E1E6 8D D9   JUMP   BSR    BAD2     GET LOCATION OF JUMP
02970 E1E8 6E 00          JMP    X        GO TO USER'S PROGRAM

02990              * PRINT CONTENTS OF STACK
03000 E1EA FE A008 PRINT  LDX    SP
03010 E1ED 08             INX
03020 E1EE 8D 44          BSR    OUT2     CONDITION CODES
03030 E1F0 8D 42          BSR    OUT2     B ACCUMULATOR
03040 E1F2 8D 40          BSR    OUT2     A ACCUMULATOR
03050 E1F4 8D 3C          BSR    OUTT4    INDEX REGISTER
03060 E1F6 8D 3A          BSR    OUTT4    PROGRAM COUNTER
03070 E1F8 CE A008        LDX    #SP
03080 E1FB 7D A011        TST    TFLAG
03090 E1FE 26 21          BNE    PRINTS   IF IN TRACE MODE
03100 E200 8D 30          BSR    OUTT4    STACK POINTER
03110 E202 B6 A014        LDA A  BKFLG    GET INSTR TO REPLACE BKPNT
03120 E205 27 05          BEQ    C2       NO BREAKPOINT SET
03130 E207 FE A068        LDX    PB2
03140 E20A A7 00          STA A  X        REPLACE BREAKPOINT
03150 E20C 7E E0E3 C2     JMP    CONTRL

03170 E20F 8D 8C   IFILL  BSR    LIMITS   GET START & END ADDRESSES
03180 E211 8D 7F          BSR    BYT      GET DESIRED CONTENTS
03190 E213 FE A002        LDX    BEGA     1ST ADDRESS TO INDEX REG
03200 E216 09             DEX
03210 E217 08      FILLOP INX
03220 E218 A7 00          STA A  X        FILL MEMORY FROM A REG
03230 E21A BC A004        CPX    ENDA
03240 E21D 26 F8          BNE    FILLOP   LOOP UNTIL DONE
03250 E21F 20 EB   C5      BRA    C2       GO TO CONTROL

03270 E221 E6 00   PRINTS LDA B  X        WHEN IN TRACE MODE
03280 E223 A6 01          LDA A  1,X      DISPLAY S-POINTER THAT
03290 E225 8B 07          ADD A  #7       WILL BE USED WHEN EXECUTING
03300 E227 C9 00          ADC B  #0       THE DISPLAYED INSTRUCTION
03310 E229 F7 A00E        STA B  TEMP
03320 E22C B7 A00F        STA A  TEMP+1
03330 E22F CE A00E        LDX    #TEMP
03340 E232 20 63   OUTT4  BRA    OUT4
```

```
03350 E234 7E E0CA OUT2   JMP    OUT2HS

03370              * TRACE ROUTINE
03380 E237 8D 88   TRACE  BSR    BAD2      GET START ADDRESS OF TRACE
03390 E239 8D 90          BSR    CRLF      AND SAVE IN XHI & XLOW
03400 E23B FE A008        LDX    SP
03410 E23E F6 A00C        LDA B  XHI       PUT START ADDRESS IN
03420 E241 E7 06          STA B  6,X       PROGRAM COUNTER POSITION
03430 E243 B6 A00D        LDA A  XLOW      IN STACK
03440 E246 A7 07          STA A  7,X
03450 E248 7C A011        INC    TFLAG     SET TRACE FLAG
03460 E24B 8E A060 RETURN LDS    #TSTACK   SEPARATE STACK FOR TRACE
03470 E24E 8D 9A          BSR    PRINT     DISPLAY ALL REGISTERS
03480 E250 7F A065        CLR    BFLAG     CLEAR BRANCH FLAG
03490 E253 FE A008        LDX    SP
03500 E256 EE 06          LDX    6,X       GET PROGRAM COUNTER FROM STAC
03510 E258 FF A00C        STX    XHI       AND SAVE IN XHI AND XLOW
03520 E25B BD E1CB        JSR    CRLF
03530 E25E CE A00C        LDX    #XHI
03540 E261 8D 34          BSR    OUT4      DISPLAY PROGRAM COUNTER
03550 E263 FE A00C        LDX    XHI       AND FIRST BYTE OF
03560 E266 E6 00          LDA B  X         INSTRUCTION
03570 E268 8D CA          BSR    OUT2
03580 E26A A6 00          LDA A  X         STORE 2ND BYTE OF INSTRUCTION
03590 E26C B7 A068        STA A  PB2       IN PB2 AND 3RD BYTE IN PB3
03600 E26F A6 01          LDA A  1,X       IF INSTRUCTION IS LONGER
03610 E271 B7 A069        STA A  PB3       THAN ONE BYTE
03620 E274 F7 A067        STA B  PB1
03630 E277 C1 8D          CMP B  #$8D      BSR? TEST FOR SPECIAL CODES
03640 E279 27 12          BEQ    BBR
03650 E27B C1 8C          CMP B  #$8C      CPX?
03660 E27D 27 25          BEQ    BYT3
03670 E27F C1 8E          CMP B  #$8E      LDS?
03680 E281 27 21          BEQ    BYT3
03690 E283 C1 CE          CMP B  #$CE      LDX?
03700 E285 27 1D          BEQ    BYT3
03710 E287 C4 F0          AND B  #$F0
03720 E289 C1 20          CMP B  #$20      TEST FOR RELATIVE BRANCH
03730 E28B 26 0D          BNE    NOTB      TYPE INSTRUCTIONS
03740 E28D 7C A065 BBR    INC    BFLAG     SET BRANCH FLAG
03750 E290 20 16          BRA    BYT2      TWO BYTE INSTRUCTION
03760 E292 7E E055 BYT    JMP    BYTE
03770 E295 20 88   C4     BRA    C5        GO TO CONTROL
03780 E297 7E E0C8 OUT4   JMP    OUT4HS
03790 E29A C1 60   NOTB   CMP B  #$60      IS CODE LESS THAN 60?
03800 E29C 25 0C          BCS    BYT1      YES - 1 BYTE INSTRUCTION
03810 E29E C4 30          AND B  #$30
03820 E2A0 C1 30          CMP B  #$30
03830 E2A2 26 04          BNE    BYT2      ONLY 3 BYTE WILL FALL THRU
03840 E2A4 8D F1   BYT3   BSR    OUT4      DISPLAY 2 BYTE OPERAND
03850 E2A6 20 02          BRA    BYT1
03860 E2A8 8D 8A   BYT2   BSR    OUT2      DISPLAY 1 BYTE OPERAND
03870 E2AA FF A00C BYT1   STX    XHI       SAVE LOCATION OF NEXT INSTR
03880              * XHI NOW CONTAINS NEXT INS LOCATION
```

```
03890 E2AD 7D A065          TST    BFLAG    IS IT A BRANCH?
03900 E2B0 27 19            BEQ    NOTBB    NO
03910 E2B2 4F               CLR A           YES, COMPUTE TARGET LOCATION
03920 E2B3 F6 A068          LDA B  PB2
03930 E2B6 2C 02            BGE    DPOS     TEST FOR BRANCH BACK
03940 E2B8 86 FF            LDA A  #$FF     FF FOR BACKWARD BRANCH
03950 E2BA FB A00D DPOS     ADD B  XLOW     ADD OPERAND TO LOWER
03960 E2BD B9 A00C          ADC A  XHI      8 BITS OF PROGRAM COUNTER
03970 E2C0 B7 A061          STA A  BPOINT   SAVE TARGET ADDRESS
03980 E2C3 F7 A062          STA B  BPOINT+1
03990 E2C6 CE A061          LDX    #BPOINT  DISPLAY TARGET ADDRESS
04000 E2C9 8D CC            BSR    OUT4
04010 E2CB BD E1CB NOTBB    JSR    CRLF
04020 E2CE BD E1AC          JSR    INEEE    GET COMMAND
04030 E2D1 16               TAB             SAVE IN B REGISTER
04040 E2D2 BD E0CC          JSR    OUTS
04050 E2D5 C1 20            CMP B  #$20     IF SPACE EXECUTE THE
04060 E2D7 27 35            BEQ    DOT      INSTRUCTION. IF NOT A
04070 E2D9 FE A008 CKCBA    LDX    SP       SPACE, TEST FOR A CHANGE
04080 E2DC 08               INX             REGISTER COMMAND.  NOTE, THIS
04090 E2DD C1 43            CMP B  #'C      PART OF MEMORY IS SHARED
04100 E2DF 27 0A            BEQ    RDC      WITH THE CHANGE REGISTER
04110 E2E1 08               INX             COMMANDS WHEN NOT IN TRACE
04120 E2E2 C1 42            CMP B  #'B      MODE.  IF IT IS A CHANGE
04130 E2E4 27 05            BEQ    RDC      REGISTER COMMAND WHILE IN
04140 E2E6 08               INX             TRACE MODE, RETURN TO
04150 E2E7 C1 41            CMP B  #'A      NOTBB FOR NEXT COMMAND.
04160 E2E9 26 0A            BNE    CHKX
04170 E2EB BD E0CA RDC      JSR    OUT2HS   DISPLAY REGISTER CONTENTS
04180 E2EE 09               DEX             SAVED IN STACK
04190 E2EF 8D A1            BSR    BYT      GET NEW CONTENTS
04200 E2F1 A7 00            STA A  X        AND STORE IN STACK
04210 E2F3 20 12            BRA    RETDID
04220 E2F5 C1 58    CHKX    CMP B  #'X
04230 E2F7 26 9C            BNE    C4
04240 E2F9 08               INX
04250 E2FA 8D 9B            BSR    OUT4     DISPLAY INDEX CONTENTS
04260 E2FC 8D 94            BSR    BYT      GET HIGH 8 BITS
04270 E2FE FE A008          LDX    SP
04280 E301 A7 04            STA A  4,X      STORE IN STACK
04290 E303 8D 8D            BSR    BYT      GET LOWER 8 BITS
04300 E305 A7 05            STA A  5,X      STORE
04310 E307 7D A011 RETDID   TST    TFLAG    IN TRACE?
04320 E30A 26 BF            BNE    NOTBB    YES, GET NEXT TRACE CMD
04330 E30C 20 87    RETNOT  BRA    C4       RETURN TO CONTROL
04340 E30E C6 3F    DOT     LDA B  #$3F     SWI CODE TO B-REG
04350 E310 B6 A067          LDA A  PB1      GET INSTRUCTION
04360 E313 81 8D            CMP A  #$8D     IS IT A BSR?
04370 E315 26 0B            BNE    TSTB     IF YES, NEXT INSTRUCTION
04380 E317 FE A061          LDX    BPOINT   WILL BE AT ADDRESS STORED
04390 E31A FF A00C          STX    XHI      IN BPOINT.
04400 E31D 7F A065          CLR    BFLAG    ONLY ONE SWI NEED BE SET
04410 E320 20 59            BRA    EXEC     SET BKPOINT AND EXECUTE INST
04420 E322 7D A065 TSTB     TST    BFLAG    IS IT CONDITIONAL BRANCH?
```

```
04430 E325 27 0C          BEQ    TSTJ      YES, SET BREAKPOINT AT
04440 E327 FE A061        LDX    BPOINT    TARGET ADDRESS IN CASE
04450 E32A A6 00          LDA A  X         PROGRAM GOES THERE.
04460 E32C B7 A063        STA A  BPOINT+2  SAVE INSTRUCTION
04470 E32F E7 00          STA B  X         SET SWI AT TARGET ADDRESS
04480 E331 20 48          BRA    EXEC
04490 E333 81 6E   TSTJ   CMP A  #$6E      INDEXED JUMP INSTRUCTION?
04500 E335 27 14          BEQ    ISX
04510 E337 81 AD          CMP A  #$AD      INDEXED JSR?
04520 E339 27 10          BEQ    ISX
04530 E33B 81 7E          CMP A  #$7E      STRAIGHT JUMP?
04540 E33D 27 04          BEQ    ISJ
04550 E33F 81 BD          CMP A  #$BD      STRAIGHT JSR?
04560 E341 26 1C          BNE    NOTJ
04570 E343 FE A068 ISJ    LDX    PB2       PUT NEXT INSTRUCTION
04580 E346 FF A00C        STX    XHI       ADDRESS IN XHI & XLOW
04590 E349 20 30          BRA    EXEC
04600 E34B FE A008 ISX    LDX    SP        COMPUTE NEXT INST ADDRESS
04610 E34E A6 05          LDA A  5,X       FOR INDEXED JUMPS
04620 E350 BB A068        ADD A  PB2
04630 E353 B7 A00D        STA A  XLOW
04640 E356 A6 04          LDA A  4,X
04650 E358 89 00          ADC A  #0
04660 E35A B7 A00C        STA A  XHI
04670 E35D 20 1C          BRA    EXEC
04680 E35F FE A008 NOTJ   LDX    SP
04690 E362 81 39          CMP A  #$39      IS INSTRUCTION AN RTS?
04700 E364 26 04          BNE    NOTRTS    NO
04710 E366 EE 08          LDX    8,X       YES, PULL RETURN ADDRESS
04720 E368 20 06          BRA    EXR       FROM STACK AND STORE IN
04730 E36A 81 38   NOTRTS CMP A  #$38      NEXT INSTRUCTION POINTER.
04740 E36C 26 05          BNE    NOTRTI
04750 E36E EE 0D          LDX    13,X
04760 E370 FF A00C EXR    STX    XHI
04770 E373 81 3F   NOTRTI CMP A  #$3F      SWI?
04780 E375 27 95          BEQ    RETNOT    YES, RETURN TO CONTROL
04790 E377 81 3E          CMP A  #$3E      WAI?
04800 E379 27 91          BEQ    RETNOT    YES, RETURN TO CONTROL
04810 E37B FE A00C EXEC   LDX    XHI       SET BREAKPOINT AT NEXT
04820 E37E A6 00          LDA A  X         INSTRUCTION LOCATION AND SAVE
04830 E380 B7 A066        STA A  OPSAVE    OP CODE.
04840 E383 E7 00          STA B  X         STORE SWI AT BREAKPOINT &
04850 E385 E1 00          CMP B  X         VERIFY THAT IT'S WITHIN RAM
04860 E387 26 83          BNE    RETNOT    IF ROM, GO TO CONTROL
04870                * EXECUTE INSTRUCTION
04880 E389 7E E199        JMP    CONTG     RTI TO EXECUTE INSTRUCTION

04900               *RETURN HERE ON SWI IF TRACE FLAG ON
04910 E38C FE A00C SWTURN LDX    XHI
04920 E38F B6 A066        LDA A  OPSAVE
04930 E392 A7 00          STA A  X         REPLACE SWI'S WITH PREVIOUS
04940 E394 7D A065        TST    BFLAG     CONTENTS.  IF BFLAG IS CLEAR,
04950 E397 27 08          BEQ    DISPLY    THEN ONLY ONE BREAKPOINT
04960 E399 FE A061        LDX    BPOINT    WAS SET.
```

```
04970 E39C B6 A063        LDA A  BPOINT+2
04980 E39F A7 00          STA A  X
04990 E3A1 7E E24B DISPLY JMP    RETURN   DISPLAY REGISTER STATUS

05010 E3A4 0D      CRLFAS FCB    $D,$A,0,0,0,4,'S,'1,4
      E3A5 0A
      E3A6 00
      E3A7 00
      E3A8 00
      E3A9 04
      E3AA 53
      E3AB 31
      E3AC 04

05030 E3AD 81 55   TDEX   CMP A  #'U       IF IT'S A "U"
05040 E3AF 27 0A          BEQ    CHA71     GET PREVIOUS ADDRESS
05050 E3B1 BD E0AC        JSR    INHEX+2   IF NOT HEX, JMP CONTROL
05060 E3B4 BD E057        JSR    BYTE+2    ELSE, GET NEW DATA
05070 E3B7 09             DEX
05080 E3B8 7E E0A2        JMP    CHA61     STORE NEW DATA
05090 E3BB 09      CHA71  DEX               GET PREVIOUS ADDRESS
05100 E3BC 09             DEX
05110 E3BD FF A00C        STX    XHI
05120 E3C0 7E E087        JMP    CHA51     PRINT PREVIOUS ADDRESS

05140      E3C3   FUTABL EQU    *         COMMAND LOOKUP TABLE
05150 E3C3 4D             FCC    /M/
05160 E3C4 E085           FDB    CHANGE    MEMORY EXAMINE
05170 E3C6 47             FCC    /G/
05180 E3C7 E199           FDB    CONTG     GO TO $A048
05190 E3C9 52             FCC    /R/
05200 E3CA E1EA           FDB    PRINT     PRINT REGISTERS
05210 E3CC 54             FCC    /T/
05220 E3CD E237           FDB    TRACE     TRACE ROUTINE
05230 E3CF 49             FCC    /I/
05240 E3D0 E20F           FDB    IFILL     MEMORY FILL
05250 E3D2 4B             FCC    /K/
05260 E3D3 E189           FDB    BKPNT     SET BREAKPOINT
05270 E3D5 34             FCC    /4/
05280 E3D6 E400           FDB    $E400     GO TO $E400
05290 E3D8 4A             FCC    /J/
05300 E3D9 E1E6           FDB    JUMP      JUMP TO ADDRESS ENTERED
05310 E3DB 51             FCC    /Q/
05320 E3DC 8020           FDB    $8020     QUICKSTART - BOOT DISC
05330 E3DE 44             FCC    /D/
05340 E3DF 7283           FDB    $7283     DISC WARMSTART
05350 E3E1 48             FCC    /H/
05360 E3E2 E1C5           FDB    PRNTON    SET HARDCOPY FLAG
05370 E3E4 4C             FCC    /L/
05380 E3E5 E00A           FDB    LOAD      LOAD ASCII FORMATTED TAPE
05390 E3E7 50             FCC    /P/
05400 E3E8 E127           FDB    PUNCH     PUNCH ASCII FORMATTED TAPE
05410 E3EA 45             FCC    /E/
05420 E3EB E1C4           FDB    ECHON     TURN INPUT ECHO ON
```

```
05430 E3ED 4E              FCC    /N/
05440 E3EE E1C6            FDB    ECHOFF   TURN INPUT ECHO OFF
05450      E3F0    TBLEND  EQU    *

05470 E3F0 13      MCLOFF  FCB    $13
05480 E3F1 0D      MCL     FCB    $D,$A,$14,0,0,'*,4
      E3F2 0A
      E3F3 14
      E3F4 00
      E3F5 00
      E3F6 2A
      E3F7 04

05500 E3F8 E000            FDB    IO       IRQ VECTOR
05510 E3FA E113            FDB    SFE      SWI VECTOR
05520 E3FC E005            FDB    POWDWN   NMI VECTOR
05530 E3FE E0D0            FDB    START    RESET VECTOR

05550                * RAM STORAGE LOCATIONS

05570 A000                 ORG    $A000
05580 A000 0002    IOV     RMB    2        I/O INTERRUPT POINTER
05590 A002 0002    BEGA    RMB    2        BEGINNING ADDRESS
05600 A004 0002    ENDA    RMB    2        ENDING ADDRESS
05610 A006 0002    NIO     RMB    2        NMI INTERRUPT POINTER
05620 A008 0002    SP      RMB    2        TARGET STACK POINTER
05630 A00A 0001    ACIAT   RMB    1        ACIA STATUS WORD
05640 A00B 0001    ECHO    RMB    1        ECHO FLAG
05650 A00C 0001    XHI     RMB    1        INDEX REG HI
05660 A00D 0001    XLOW    RMB    1        INDEX REG LOW
05670 A00E 0001    TEMP    RMB    1        TEMP
05680 A00F 0002    TW      RMB    2        TEMP
05690 A011 0001    TFLAG   RMB    1        TRACE FLAG
05700 A012 0002    XTEMP   RMB    2        X-REG TEMP STORAGE
05710 A014 0001    BKFLG   RMB    1        BREAKPOINT FLAG
05720 A015 002D            RMB    45       SMARTBUG STACK
05730 A042 0001    STACK   RMB    1        STACK POINTER
05740 A043 001D            RMB    29
05750 A060 0001    TSTACK  RMB    1        TRACE MODE STACK
05760 A061 0003    BPOINT  RMB    3        BRANCH POINT ADDR & CODE
05770 A064 0001    MCONT   RMB    1        TEMP
05780 A065 0001    BFLAG   RMB    1        BRANCH FLAG (TRACE)
05790 A066 0001    OPSAVE  RMB    1        OPERAND (TRACE)
05800 A067 0001    PB1     RMB    1        TRACE TEMP
05810 A068 0001    PB2     RMB    1        TRACE TEMP
05820 A069 0001    PB3     RMB    1        TRACE TEMP
05830 A06A 0001    CKSM    RMB    1        CHECKSUM
05840 A06B 0001    BYTECT  RMB    1        BYTE COUNT
05850      A04A    PRINTR  EQU    $A04A    USER PRINT ROUTINE
```

```
05870
ACIAS  8008
ACIAD  8009
IO     E000
POWDWN E005
LOAD   E00A
LOAD3  E013
LOAD11 E02F
LOAD15 E03B
LOAD19 E040
LOAD21 E044
C1     E044
BADDR  E047
BYTE   E055
OUTHL  E067
OUTHR  E06B
OUTCH  E075
INCH   E078
PDATA2 E07B
PDATA1 E07E
CHANGE E085
CHA51  E087
CHA61  E0A2
INHEX  E0AA
IN1HG  E0BE
OUT2H  E0BF
OUT2HA E0C1
OUT4HS E0C8
OUT2HS E0CA
OUTS   E0CC
START  E0D0
INZ    E0DE
INZ1   E0E0
CONTRL E0E3
NXTCHR E0FF
GOODCH E10E
SFE    E113
PUNCH  E127
PUN11  E134
PUN22  E146
PUN23  E148
PUN32  E167
PUNT2  E182
PRNT   E187
BKPNT  E189
CONTG  E199
LIMITS E19D
OUS    E1A9
INEEE  E1AC
BAD2   E1C1
ECHON  E1C4
PRNTON E1C5
ECHOFF E1C6
C3     E1C9
```

END

```
CRLF   E1CB
PDAT1  E1CE
OUTEEE E1D1
OUTCH2 E1D9
OUTCH1 E1DA
JUMP   E1E6
PRINT  E1EA
C2     E20C
IFILL  E20F
FILLOP E217
C5     E21F
PRINTS E221
OUTT4  E232
OUT2   E234
TRACE  E237
RETURN E24B
BBR    E28D
BYT    E292
C4     E295
OUT4   E297
NOTB   E29A
BYT3   E2A4
BYT2   E2A8
BYT1   E2AA
DPOS   E2BA
NOTBB  E2CB
CKCBA  E2D9
RDC    E2EB
CHKX   E2F5
RETDID E307
RETNOT E30C
DOT    E30E
TSTB   E322
TSTJ   E333
ISJ    E343
ISX    E34B
NOTJ   E35F
NOTRTS E36A
EXR    E370
NOTRTI E373
EXEC   E37B
SWTURN E38C
DISPLY E3A1
CRLFAS E3A4
TDEX   E3AD
CHA71  E3BB
FUTABL E3C3
TBLEND E3F0
MCLOFF E3F0
MCL    E3F1
IOV    A000
BEGA   A002
ENDA   A004
NIO    A006
```

```
SP     A008
ACIAT  A00A
ECHO   A00B
XHI    A00C
XLOW   A00D
TEMP   A00E
TW     A00F
TFLAG  A011
XTEMP  A012
BKFLG  A014
STACK  A042
TSTACK A060
BPOINT A061
MCONT  A064
BFLAG  A065
OPSAVE A066
PB1    A067
PB2    A068
PB3    A069
CKSM   A06A
BYTECT A06B
PRINTR A04A

TOTAL ERRORS 00000
```